Data sheet

6ES7534-7QE00-0AB0



SIMATIC S7-1500 Analog input/output module AI 4x U/I/R/RTD/TC ST; 4 channels in groups of 4; Hardware interrupts; Diagnostics AQ 2x U/I ST; 2 channels in groups of 2; Substitute value; Diagnostics Common mode voltage approx. 10 V 16 bit; Accuracy 0.3%; Delivery including push-in front connector, infeed element, shield bracket and shield terminal

General information	
Product type designation	AI 4xU/I/RTD/TC /AQ 2xU/I ST
HW functional status	FS01
Firmware version	V1.0.0
 FW update possible 	Yes
Product function	
 I&M data 	Yes; I&M0 to I&M3
 Isochronous mode 	No
 Prioritized startup 	No
 Measuring range scalable 	No
 Scalable measured values 	No
 Adjustment of measuring range 	No
Output range scalable	No
Engineering with	
 STEP 7 TIA Portal configurable/integrated from version 	V13 / V13.0.2
 STEP 7 configurable/integrated from version 	V5.5 SP3 / -
 PROFIBUS from GSD version/GSD revision 	V1.0 / V5.1
PROFINET from GSD version/GSD revision	V2.3 / -
Operating mode	
 Oversampling 	No
• MSI	Yes
• MSO	Yes
CiR - Configuration in RUN	
Reparameterization possible in RUN	Yes
Calibration possible in RUN	Yes
Supply voltage	
Rated value (DC)	24 V
permissible range, lower limit (DC)	19.2 V
permissible range, upper limit (DC)	28.8 V
Reverse polarity protection	Yes
Input current	
Current consumption, max.	200 mA; with 24 V DC supply
Encoder supply	
24 V encoder supply	
Short-circuit protection	Yes
 Output current, max. 	20 mA; Max. 47 mA per channel for a duration < 10 s
Power	
Power available from the backplane bus	0.7 W

Power loss	
Power loss, typ.	3.3 W
Analog inputs	
Number of analog inputs	4
For current measurement	4
For voltage measurement	4
For resistance/resistance thermometer	2
measurement	
 For thermocouple measurement 	4
permissible input voltage for voltage input (destruction	28.8 V
limit), max.	
permissible input current for current input (destruction	40 mA
limit), max.	450 Ohra 200 Ohra 600 Ohra B4400 B4200 Ni400, 4 25 mA, 6 000
Constant measurement current for resistance-type transmitter, typ.	150 Ohm, 300 Ohm, 600 Ohm, Pt100, Pt200, Ni100: 1.25 mA; 6 000 Ohm, Pt500, Pt1000, Ni1000, LG-Ni1000: 0.625 mA; PTC: 0.472 mA
Technical unit for temperature measurement adjustable	Yes; °C/°F/K
Analog input with oversampling	No
Standardization of measured values	No No
	INO
Input ranges (rated values), voltages • 0 to +5 V	No
	No No
● 0 to +10 V ● 1 V to 5 V	No Yes
— Input resistance (1 V to 5 V)	100 kΩ
• -1 V to +1 V	Yes
— Input resistance (-1 V to +1 V)	10 ΜΩ
• -10 V to +10 V	Yes
— Input resistance (-10 V to +10 V)	100 kΩ
• -2.5 V to +2.5 V	Yes
— Input resistance (-2.5 V to +2.5 V)	10 ΜΩ
• -25 mV to +25 mV	No
● -250 mV to +250 mV	Yes
— Input resistance (-250 mV to +250 mV)	10 ΜΩ
• -5 V to +5 V	Yes
— Input resistance (-5 V to +5 V)	100 kΩ
• -50 mV to +50 mV	Yes
— Input resistance (-50 mV to +50 mV)	10 ΜΩ
• -500 mV to +500 mV	Yes
— Input resistance (-500 mV to +500 mV)	10 ΜΩ
• -80 mV to +80 mV	Yes
— Input resistance (-80 mV to +80 mV)	10 ΜΩ
Input ranges (rated values), currents	
• 0 to 20 mA	Yes
— Input resistance (0 to 20 mA)	25 Ω ; Plus approx. 42 ohms for overvoltage protection by PTC
• -20 mA to +20 mA	Yes
— Input resistance (-20 mA to +20 mA)	25 Ω ; Plus approx. 42 ohms for overvoltage protection by PTC
• 4 mA to 20 mA	Yes
— Input resistance (4 mA to 20 mA)	25 Ω ; Plus approx. 42 ohms for overvoltage protection by PTC
Input ranges (rated values), thermocouples	
• Type B	Yes
— Input resistance (Type B)	10 ΜΩ
• Type C	No
• Type E	Yes
— Input resistance (Type E)	10 ΜΩ
• Type J	Yes
Input resistance (type J)	10 ΜΩ
• Type K	Yes
— Input resistance (Type K)	10 MΩ
• Type L	No
• Type N	Yes
— Input resistance (Type N)	10 MΩ
	Yes
Type R	163

Input registance (Type D)	10 ΜΩ
— Input resistance (Type R)● Type S	Yes
	10 ΜΩ
— Input resistance (Type S)	Yes
• Type T	
— Input resistance (Type T)	10 ΜΩ
• Type U	No No
Type TXK/TXK(L) to GOST Type Txk/Txk(L) to GOST Type Txk/Txk(L) to GOST	No
Input ranges (rated values), resistance thermometer	N-
• Cu 10	No
Cu 10 according to GOST	No No
• Cu 50	No
Cu 50 according to GOST	No
• Cu 100	No
 Cu 100 according to GOST 	No
• Ni 10	No
 Ni 10 according to GOST 	No
• Ni 100	Yes; Standard/climate
— Input resistance (Ni 100)	10 ΜΩ
 Ni 100 according to GOST 	No
• Ni 1000	Yes; Standard/climate
— Input resistance (Ni 1000)	10 ΜΩ
 Ni 1000 according to GOST 	No
• LG-Ni 1000	Yes; Standard/climate
— Input resistance (LG-Ni 1000)	10 ΜΩ
• Ni 120	No
 Ni 120 according to GOST 	No
• Ni 200	No
 Ni 200 according to GOST 	No
• Ni 500	No
 Ni 500 according to GOST 	No
• Pt 10	No
 Pt 10 according to GOST 	No
• Pt 50	No
 Pt 50 according to GOST 	No
• Pt 100	Yes; Standard/climate
— Input resistance (Pt 100)	10 ΜΩ
 Pt 100 according to GOST 	No
• Pt 1000	Yes; Standard/climate
— Input resistance (Pt 1000)	10 ΜΩ
Pt 1000 according to GOST	No
• Pt 200	Yes; Standard/climate
— Input resistance (Pt 200)	10 ΜΩ
Pt 200 according to GOST	No
• Pt 500	Yes; Standard/climate
— Input resistance (Pt 500)	10 ΜΩ
Pt 500 according to GOST	No
Input ranges (rated values), resistors	
• 0 to 150 ohms	Yes
— Input resistance (0 to 150 ohms)	10 ΜΩ
• 0 to 300 ohms	Yes
— Input resistance (0 to 300 ohms)	10 ΜΩ
• 0 to 600 ohms	Yes
— Input resistance (0 to 600 ohms)	10 ΜΩ
• 0 to 3000 ohms	No
• 0 to 6000 ohms	Yes
Input resistance (0 to 6000 ohms)	10 ΜΩ
PTC	Yes
— Input resistance (PTC)	10 MΩ
Thermocouple (TC)	1 ♦ 18/177
Temperature compensation	

managed to the	V
— parameterizable	Yes
— internal temperature compensation	Yes
 external temperature compensation via RTD 	Yes
Compensation for 0 °C reference point	Yes; fixed value can be set
temperature	No
— Reference channel of the module	No
Cable length	000 mg for 11/1 2000 mg for D/DTD 50 mg for TC
• shielded, max.	800 m; for U/I, 200 m for R/RTD, 50 m for TC
Analog outputs	
Number of analog outputs	2
Voltage output, short-circuit protection	Yes
Voltage output, short-circuit current, max.	24 mA
Current output, no-load voltage, max.	22 V
Cycle time (all channels), min.	3.2 ms; ±0.5 ms, regardless of the number of activated channels
Output ranges, voltage	
• 0 to 10 V	Yes
• 1 V to 5 V	Yes
• -5 V to +5 V	No
• -10 V to +10 V	Yes
Output ranges, current	
• 0 to 20 mA	Yes
• -20 mA to +20 mA	Yes
• 4 mA to 20 mA	Yes
Connection of actuators	
 for voltage output two-wire connection 	Yes
 for voltage output four-wire connection 	Yes
for current output two-wire connection	Yes
Load impedance (in rated range of output)	
with voltage outputs, min.	1 k Ω ; 0.5 kOhm at 1 to 5 V
 with voltage outputs, capacitive load, max. 	1 μF
 with current outputs, max. 	750 Ω
with current outputs, inductive load, max.	10 mH
Cable length	
shielded, max.	800 m; for current, 200 m for voltage
Analog value generation for the inputs	
Integration and conversion time/resolution per channel	
	16 bit
 Resolution with overrange (bit including sign), max. 	
 Resolution with overrange (bit including sign), max. Integration time, parameterizable 	Yes
	Yes 2,5 / 16,67 / 20 / 100 ms
Integration time, parameterizableIntegration time (ms)	
Integration time, parameterizable	2,5 / 16,67 / 20 / 100 ms
Integration time, parameterizableIntegration time (ms)Basic conversion time, including integration time	2,5 / 16,67 / 20 / 100 ms
 Integration time, parameterizable Integration time (ms) Basic conversion time, including integration time (ms) — additional conversion time for wire-break 	2,5 / 16,67 / 20 / 100 ms 9 / 23 / 27 / 107 ms 9 ms 150 ohm, 300 ohm, 600 ohm, Pt100, Pt200, Ni100: 2 ms, 6000 ohm,
 Integration time, parameterizable Integration time (ms) Basic conversion time, including integration time (ms) additional conversion time for wire-break monitoring additional conversion time for resistance measurement 	2,5 / 16,67 / 20 / 100 ms 9 / 23 / 27 / 107 ms 9 ms
 Integration time, parameterizable Integration time (ms) Basic conversion time, including integration time (ms) additional conversion time for wire-break monitoring additional conversion time for resistance measurement Interference voltage suppression for interference 	2,5 / 16,67 / 20 / 100 ms 9 / 23 / 27 / 107 ms 9 ms 150 ohm, 300 ohm, 600 ohm, Pt100, Pt200, Ni100: 2 ms, 6000 ohm,
 Integration time, parameterizable Integration time (ms) Basic conversion time, including integration time (ms) additional conversion time for wire-break monitoring additional conversion time for resistance measurement Interference voltage suppression for interference frequency f1 in Hz 	2,5 / 16,67 / 20 / 100 ms 9 / 23 / 27 / 107 ms 9 ms 150 ohm, 300 ohm, 600 ohm, Pt100, Pt200, Ni100: 2 ms, 6000 ohm, Pt500, Pt1000, Ni1000, LG-Ni1000, PTC: 4 ms 400 / 60 / 50 / 10
 Integration time, parameterizable Integration time (ms) Basic conversion time, including integration time (ms) additional conversion time for wire-break monitoring additional conversion time for resistance measurement Interference voltage suppression for interference frequency f1 in Hz Time for offset calibration (per module) 	2,5 / 16,67 / 20 / 100 ms 9 / 23 / 27 / 107 ms 9 ms 150 ohm, 300 ohm, 600 ohm, Pt100, Pt200, Ni100: 2 ms, 6000 ohm, Pt500, Pt1000, Ni1000, LG-Ni1000, PTC: 4 ms
 Integration time, parameterizable Integration time (ms) Basic conversion time, including integration time (ms) additional conversion time for wire-break monitoring additional conversion time for resistance measurement Interference voltage suppression for interference frequency f1 in Hz Time for offset calibration (per module) Smoothing of measured values 	2,5 / 16,67 / 20 / 100 ms 9 / 23 / 27 / 107 ms 9 ms 150 ohm, 300 ohm, 600 ohm, Pt100, Pt200, Ni100: 2 ms, 6000 ohm, Pt500, Pt1000, Ni1000, LG-Ni1000, PTC: 4 ms 400 / 60 / 50 / 10 Basic conversion time of the slowest channel
 Integration time, parameterizable Integration time (ms) Basic conversion time, including integration time (ms) additional conversion time for wire-break monitoring additional conversion time for resistance measurement Interference voltage suppression for interference frequency f1 in Hz Time for offset calibration (per module) Smoothing of measured values parameterizable 	2,5 / 16,67 / 20 / 100 ms 9 / 23 / 27 / 107 ms 9 ms 150 ohm, 300 ohm, 600 ohm, Pt100, Pt200, Ni100: 2 ms, 6000 ohm, Pt500, Pt1000, Ni1000, LG-Ni1000, PTC: 4 ms 400 / 60 / 50 / 10 Basic conversion time of the slowest channel
 Integration time, parameterizable Integration time (ms) Basic conversion time, including integration time (ms) additional conversion time for wire-break monitoring additional conversion time for resistance measurement Interference voltage suppression for interference frequency f1 in Hz Time for offset calibration (per module) Smoothing of measured values parameterizable Step: None 	2,5 / 16,67 / 20 / 100 ms 9 / 23 / 27 / 107 ms 9 ms 150 ohm, 300 ohm, 600 ohm, Pt100, Pt200, Ni100: 2 ms, 6000 ohm, Pt500, Pt1000, Ni1000, LG-Ni1000, PTC: 4 ms 400 / 60 / 50 / 10 Basic conversion time of the slowest channel Yes Yes
 Integration time, parameterizable Integration time (ms) Basic conversion time, including integration time (ms) additional conversion time for wire-break monitoring additional conversion time for resistance measurement Interference voltage suppression for interference frequency f1 in Hz Time for offset calibration (per module) Smoothing of measured values parameterizable Step: None Step: low 	2,5 / 16,67 / 20 / 100 ms 9 / 23 / 27 / 107 ms 9 ms 150 ohm, 300 ohm, 600 ohm, Pt100, Pt200, Ni100: 2 ms, 6000 ohm, Pt500, Pt1000, Ni1000, LG-Ni1000, PTC: 4 ms 400 / 60 / 50 / 10 Basic conversion time of the slowest channel Yes Yes Yes
Integration time, parameterizable Integration time (ms) Basic conversion time, including integration time (ms) — additional conversion time for wire-break monitoring — additional conversion time for resistance measurement Interference voltage suppression for interference frequency f1 in Hz Time for offset calibration (per module) Smoothing of measured values parameterizable Step: None Step: low Step: Medium	2,5 / 16,67 / 20 / 100 ms 9 / 23 / 27 / 107 ms 9 ms 150 ohm, 300 ohm, 600 ohm, Pt100, Pt200, Ni100: 2 ms, 6000 ohm, Pt500, Pt1000, Ni1000, LG-Ni1000, PTC: 4 ms 400 / 60 / 50 / 10 Basic conversion time of the slowest channel Yes Yes Yes Yes
Integration time, parameterizable Integration time (ms) Basic conversion time, including integration time (ms) — additional conversion time for wire-break monitoring — additional conversion time for resistance measurement Interference voltage suppression for interference frequency f1 in Hz Time for offset calibration (per module) Smoothing of measured values parameterizable Step: None Step: low Step: Medium Step: High	2,5 / 16,67 / 20 / 100 ms 9 / 23 / 27 / 107 ms 9 ms 150 ohm, 300 ohm, 600 ohm, Pt100, Pt200, Ni100: 2 ms, 6000 ohm, Pt500, Pt1000, Ni1000, LG-Ni1000, PTC: 4 ms 400 / 60 / 50 / 10 Basic conversion time of the slowest channel Yes Yes Yes
Integration time, parameterizable Integration time (ms) Basic conversion time, including integration time (ms) — additional conversion time for wire-break monitoring — additional conversion time for resistance measurement Interference voltage suppression for interference frequency f1 in Hz Time for offset calibration (per module) Smoothing of measured values parameterizable Step: None Step: low Step: Medium	2,5 / 16,67 / 20 / 100 ms 9 / 23 / 27 / 107 ms 9 ms 150 ohm, 300 ohm, 600 ohm, Pt100, Pt200, Ni100: 2 ms, 6000 ohm, Pt500, Pt1000, Ni1000, LG-Ni1000, PTC: 4 ms 400 / 60 / 50 / 10 Basic conversion time of the slowest channel Yes Yes Yes Yes
Integration time, parameterizable Integration time (ms) Basic conversion time, including integration time (ms) — additional conversion time for wire-break monitoring — additional conversion time for resistance measurement Interference voltage suppression for interference frequency f1 in Hz Time for offset calibration (per module) Smoothing of measured values parameterizable Step: None Step: low Step: Medium Step: High	2,5 / 16,67 / 20 / 100 ms 9 / 23 / 27 / 107 ms 9 ms 150 ohm, 300 ohm, 600 ohm, Pt100, Pt200, Ni100: 2 ms, 6000 ohm, Pt500, Pt1000, Ni1000, LG-Ni1000, PTC: 4 ms 400 / 60 / 50 / 10 Basic conversion time of the slowest channel Yes Yes Yes Yes
Integration time, parameterizable Integration time (ms) Basic conversion time, including integration time (ms) — additional conversion time for wire-break monitoring — additional conversion time for resistance measurement Interference voltage suppression for interference frequency f1 in Hz Time for offset calibration (per module) Smoothing of measured values parameterizable Step: None Step: None Step: low Step: High Analog value generation for the outputs	2,5 / 16,67 / 20 / 100 ms 9 / 23 / 27 / 107 ms 9 ms 150 ohm, 300 ohm, 600 ohm, Pt100, Pt200, Ni100: 2 ms, 6000 ohm, Pt500, Pt1000, Ni1000, LG-Ni1000, PTC: 4 ms 400 / 60 / 50 / 10 Basic conversion time of the slowest channel Yes Yes Yes Yes
Integration time, parameterizable Integration time (ms) Basic conversion time, including integration time (ms) — additional conversion time for wire-break monitoring — additional conversion time for resistance measurement Interference voltage suppression for interference frequency f1 in Hz Time for offset calibration (per module) Smoothing of measured values parameterizable Step: None Step: low Step: low Step: High Analog value generation for the outputs Integration and conversion time/resolution per channel	2,5 / 16,67 / 20 / 100 ms 9 / 23 / 27 / 107 ms 9 ms 150 ohm, 300 ohm, 600 ohm, Pt100, Pt200, Ni100: 2 ms, 6000 ohm, Pt500, Pt1000, Ni1000, LG-Ni1000, PTC: 4 ms 400 / 60 / 50 / 10 Basic conversion time of the slowest channel Yes Yes Yes Yes Yes
Integration time, parameterizable Integration time (ms) Basic conversion time, including integration time (ms) — additional conversion time for wire-break monitoring — additional conversion time for resistance measurement Interference voltage suppression for interference frequency f1 in Hz Time for offset calibration (per module) Smoothing of measured values parameterizable Step: None Step: None Step: low Step: Medium Step: High Analog value generation for the outputs Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max.	2,5 / 16,67 / 20 / 100 ms 9 / 23 / 27 / 107 ms 9 ms 150 ohm, 300 ohm, 600 ohm, Pt100, Pt200, Ni100: 2 ms, 6000 ohm, Pt500, Pt1000, Ni1000, LG-Ni1000, PTC: 4 ms 400 / 60 / 50 / 10 Basic conversion time of the slowest channel Yes Yes Yes Yes Yes Yes
 Integration time, parameterizable Integration time (ms) Basic conversion time, including integration time (ms) additional conversion time for wire-break monitoring additional conversion time for resistance measurement Interference voltage suppression for interference frequency f1 in Hz Time for offset calibration (per module) Smoothing of measured values parameterizable Step: None Step: low Step: High Analog value generation for the outputs Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Conversion time (per channel) 	2,5 / 16,67 / 20 / 100 ms 9 / 23 / 27 / 107 ms 9 ms 150 ohm, 300 ohm, 600 ohm, Pt100, Pt200, Ni100: 2 ms, 6000 ohm, Pt500, Pt1000, Ni1000, LG-Ni1000, PTC: 4 ms 400 / 60 / 50 / 10 Basic conversion time of the slowest channel Yes Yes Yes Yes Yes Yes
Integration time, parameterizable Integration time (ms) Basic conversion time, including integration time (ms) — additional conversion time for wire-break monitoring — additional conversion time for resistance measurement Interference voltage suppression for interference frequency f1 in Hz Time for offset calibration (per module) Smoothing of measured values parameterizable Step: None Step: None Step: low Step: High Analog value generation for the outputs Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Conversion time (per channel) Settling time	2,5 / 16,67 / 20 / 100 ms 9 / 23 / 27 / 107 ms 9 ms 150 ohm, 300 ohm, 600 ohm, Pt100, Pt200, Ni100: 2 ms, 6000 ohm, Pt500, Pt1000, Ni1000, LG-Ni1000, PTC: 4 ms 400 / 60 / 50 / 10 Basic conversion time of the slowest channel Yes Yes Yes Yes Yes Yes Yes Yes Yes Ye

for inductive load	2.5 ms
Encoder	
Connection of signal encoders	
for voltage measurement	Yes
• for current measurement as 2-wire transducer	Yes
 Burden of 2-wire transmitter, max. 	820 Ω
 for current measurement as 4-wire transducer 	Yes
 for resistance measurement with two-wire 	Yes; Only for PTC
connection	
 for resistance measurement with three-wire connection 	Yes; All measuring ranges except PTC; internal compensation of the cable resistances
for resistance measurement with four-wire connection	Yes; All measuring ranges except PTC
Errors/accuracies	
Linearity error (relative to input range), (+/-)	0.02 %
Temperature error (relative to input range), (+/-)	0.005 %/K; With TC type T 0.02 ± % / K
Crosstalk between the inputs, max.	-80 dB
Repeat accuracy in steady state at 25 °C (relative to input	0.02 %
range), (+/-)	
Output ripple (relative to output range, bandwidth 0 to 50 kHz), (+/-)	0.02 %
Linearity error (relative to output range), (+/-)	0.15 %
Temperature error (relative to output range), (+/-)	0.002 %/K
Crosstalk between the outputs, max.	-100 dB
Repeat accuracy in steady state at 25 °C (relative to output range), (+/-)	0.05 %
Temperature error of internal compensation	±6 °C
Operational error limit in overall temperature range	0.0%
Voltage, relative to input range, (+/-)	0.3 %
Current, relative to input range, (+/-) Projector of the project range (+/-) Projector of the project range (+/-) Projector of the project range (+/-)	0.3 %
Resistance, relative to input range, (+/-) Resistance the respective to input range (+/-)	0.3 %
Resistance thermometer, relative to input range, (+/-)	0.3 %; Ptxxx standard: ±1.5 K, Ptxxx climate: ±0.5 K, Nixxx standard: ±0.5 K, Nixxx climate: ±0.3 K
 Thermocouple, relative to input range, (+/-) 	0.3 %; Type B: > 600 °C ±4.6 K, type E: > -200 °C ±1.5 K, type J: > -210 °C ±1.9 K, type K: > -200 °C ±2.4 K, type N: > -200 °C ±2.9 K, type R: > 0 °C ±4.7 K, type S: > 0 °C ±4.6 K, type T: > -200 °C ±2.4 K
 Voltage, relative to output range, (+/-) 	0.3 %
Current, relative to output range, (+/-)	0.3 %
Basic error limit (operational limit at 25 °C)	
 Voltage, relative to input range, (+/-) 	0.1 %
 Current, relative to input range, (+/-) 	0.1 %
 Resistance, relative to input range, (+/-) 	0.1 %
 Resistance thermometer, relative to input range, (+/-) 	0.1 %; Ptxxx standard: ± 0.7 K, Ptxxx climate: ± 0.2 K, Nixxx standard: ± 0.3 K, Nixxx climate: ± 0.15 K
 Thermocouple, relative to input range, (+/-) 	0.1 %; Type B: > 600 °C ±1.7 K, type E: > -200 °C ±0.7 K, type J: > -210 °C ±0.8 K, type K: > -200 °C ±1.2 K, type N: > -200 °C ±1.2 K, type R: > 0 °C ±1.9 K, type S: > 0 °C ±1.9 K, type T: > -200 °C ±0.8 K
 Voltage, relative to output range, (+/-) 	0.2 %
Current, relative to output range, (+/-)	0.2 %
Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = i	interference frequency
Series mode interference (peak value of	40 dB
interference < rated value of input range), min.	
Common mode voltage, max.	10 V
Common mode interference, min.	60 dB
Interrupts/diagnostics/status information	
Diagnostics function	Yes
Substitute values connectable	Yes
Alarms	V
Diagnostic alarm Limit and a plants	Yes
Limit value alarm	Yes; two upper and two lower limit values in each case
Diagnoses	Van
Monitoring the supply voltage Wire break	Yes
Wire-break	Yes; only for input type 1 5 V, 4 20 mA, TC, R, RTD and output

	type current
Short-circuit	Yes; Only for output type "voltage"
Overflow/underflow	Yes
Diagnostics indication LED	
• RUN LED	Yes; green LED
• ERROR LED	Yes; red LED
 Monitoring of the supply voltage (PWR-LED) 	Yes; green LED
 Channel status display 	Yes; green LED
 for channel diagnostics 	Yes; red LED
for module diagnostics	Yes; red LED
Potential separation	
Potential separation analog inputs	
 between the channels 	No
 between the channels, in groups of 	4
 between the channels and backplane bus 	Yes
Between the channels and load voltage L+	Yes
Potential separation analog outputs	
 between the channels 	No
 between the channels, in groups of 	2
 between the channels and backplane bus 	Yes
 Between the channels and load voltage L+ 	Yes
Permissible potential difference	
between the inputs (UCM)	20 V DC
Between the inputs and MANA (UCM)	10 V DC
between S- and MANA (UCM)	8 V DC
Isolation	
Isolation tested with	707 V DC (type test)
Ambient conditions	
Ambient temperature during operation	
horizontal installation, min.	0 °C
 horizontal installation, max. 	60 °C
 vertical installation, min. 	0 °C
 vertical installation, max. 	40 °C
Altitude during operation relating to sea level	
 Installation altitude above sea level, max. 	5 000 m; Restrictions for installation altitudes > 2 000 m, see manual
Dimensions	
Width	25 mm
Height	147 mm
Depth	129 mm
Weights	
Weight, approx.	250 g
Other	
Note:	Supplied incl. 40-pole push-in front connectors. Additional basic error and noise for integration time = 2.5 ms: Voltage: ±250 mV (±0.02%), ±80 mV (±0.05%), ±50 mV (±0.05%); resistance: 150 Ohms (±0.02%); resistance thermometer: Pt100 climate: ±0.08 K, Ni100 climate: ±0.08 K; thermoelement: Type B, R, S: ±3 K, type E, J, K, N, T: ±1 K
last modified:	1/20/2021 [7

last modified: 4/29/2021 🖸