## SIEMENS

## Data sheet

## 6ES7131-6BH01-2BA0



SIMATIC ET 200SP, Digital input module, DI 16x 24V DC Standard, type 3 (IEC 61131), sink input, (PNP, P-reading), Packing unit: 10 Pieces, fits to BU-type A0, Colour Code CC00, input delay time 0,05..20ms, diagnostics wire break, diagnostics supply voltage

•	
General information	
Product type designation	DI 16x24VDC ST
HW functional status	From FS02
Firmware version	V0.0
<ul> <li>FW update possible</li> </ul>	No
usable BaseUnits	BU type A0
Color code for module-specific color identification plate	CC00
Product function	
• I&M data	Yes; I&M0 to I&M3
Isochronous mode	No
Engineering with	
<ul> <li>STEP 7 TIA Portal configurable/integrated from version</li> </ul>	V14
<ul> <li>STEP 7 configurable/integrated from version</li> </ul>	V5.5 SP3
<ul> <li>PCS 7 configurable/integrated from version</li> </ul>	V8.1 SP1
<ul> <li>PROFIBUS from GSD version/GSD revision</li> </ul>	One GSD file each, Revision 3 and 5 and higher
<ul> <li>PROFINET from GSD version/GSD revision</li> </ul>	GSDML V2.3
Operating mode	
• DI	Yes
Counter	No
<ul> <li>Oversampling</li> </ul>	No
• MSI	No
Supply voltage	
Rated value (DC)	24 V
permissible range, lower limit (DC)	19.2 V
permissible range, upper limit (DC)	28.8 V
Reverse polarity protection	Yes
Input current	
Current consumption, max.	90 mA
Encoder supply	
24 V encoder supply	
• 24 V	No
Power loss	
Power loss, typ.	1.7 W
Address area	
Address space per module	
Inputs	2 byte; + 2 bytes for QI information
Hardware configuration	
Automatic encoding	Yes
Mechanical coding element	Yes
0	

Type of mechanical coding element	Туре А
Selection of BaseUnit for connection variants	
• 1-wire connection	BU type A0
<ul> <li>2-wire connection</li> </ul>	BU type A0 + Potential distributor module
<ul> <li>3-wire connection</li> </ul>	BU type A0 + Potential distributor module
<ul> <li>4-wire connection</li> </ul>	BU type A0 + Potential distributor module
Digital inputs	
Number of digital inputs	16
Digital inputs, parameterizable	Yes
Source/sink input	P-reading
Input characteristic curve in accordance with IEC 61131,	Yes
type 3	
Input voltage	
Rated value (DC)	24 V
<ul> <li>for signal "0"</li> </ul>	-30 to +5 V
• for signal "1"	+11 to +30V
Input current	
<ul> <li>for signal "1", typ.</li> </ul>	2.5 mA
Input delay (for rated value of input voltage)	
for standard inputs	
— parameterizable	Yes; 0.05 / 0.1 / 0.4 / 0.8 / 1.6 / 3.2 / 12.8 / 20 ms (in each case + delay
	of 30 to 500 µs, depending on line length)
— at "0" to "1", min.	0.05 ms
— at "0" to "1", max.	20 ms
— at "1" to "0", min.	0.05 ms
— at "1" to "0", max.	20 ms
Cable length	
<ul> <li>shielded, max.</li> </ul>	1 000 m
• unshielded, max.	600 m
Encoder	
Connectable encoders	
• 2-wire sensor	Yes
<ul> <li>– permissible quiescent current (2-wire sensor), max.</li> </ul>	1.5 mA
<ul> <li>permissible quiescent current (2-wire sensor), max.</li> </ul>	
<ul> <li>permissible quiescent current (2-wire sensor), max.</li> <li>Interrupts/diagnostics/status information</li> </ul>	1.5 mA
<ul> <li>permissible quiescent current (2-wire sensor), max.</li> <li>Interrupts/diagnostics/status information</li> <li>Diagnostics function</li> </ul>	
<ul> <li>permissible quiescent current (2-wire sensor), max.</li> <li>Interrupts/diagnostics/status information</li> <li>Diagnostics function</li> <li>Alarms</li> </ul>	1.5 mA Yes
<ul> <li>permissible quiescent current (2-wire sensor), max.</li> <li>Interrupts/diagnostics/status information</li> <li>Diagnostics function</li> <li>Alarms         <ul> <li>Diagnostic alarm</li> </ul> </li> </ul>	1.5 mA
<ul> <li>permissible quiescent current (2-wire sensor), max.</li> <li>Interrupts/diagnostics/status information</li> <li>Diagnostics function</li> <li>Alarms         <ul> <li>Diagnostic alarm</li> <li>Diagnoses</li> </ul> </li> </ul>	1.5 mA Yes Yes
<ul> <li>permissible quiescent current (2-wire sensor), max.</li> <li>Interrupts/diagnostics/status information</li> <li>Diagnostics function</li> <li>Alarms         <ul> <li>Diagnostic alarm</li> <li>Diagnoses</li> <li>Diagnostic information readable</li> </ul> </li> </ul>	1.5 mA Yes Yes
<ul> <li>permissible quiescent current (2-wire sensor), max.</li> <li>Interrupts/diagnostics/status information</li> <li>Diagnostics function</li> <li>Alarms         <ul> <li>Diagnostic alarm</li> <li>Diagnoses</li> <li>Diagnostic information readable</li> <li>Monitoring the supply voltage</li> </ul> </li> </ul>	1.5 mA Yes Yes Yes
<ul> <li>permissible quiescent current (2-wire sensor), max.</li> <li>Interrupts/diagnostics/status information</li> <li>Diagnostics function</li> <li>Alarms         <ul> <li>Diagnostic alarm</li> <li>Diagnostic alarm</li> <li>Diagnostic information readable</li> <li>Monitoring the supply voltage</li> <li>parameterizable</li> </ul> </li> </ul>	1.5 mA Yes Yes Yes Yes Yes
<ul> <li>permissible quiescent current (2-wire sensor), max.</li> <li>Interrupts/diagnostics/status information</li> <li>Diagnostics function</li> <li>Alarms         <ul> <li>Diagnostic alarm</li> <li>Diagnoses</li> <li>Diagnostic information readable</li> <li>Monitoring the supply voltage</li></ul></li></ul>	1.5 mA Yes Yes Yes Yes No
<ul> <li>permissible quiescent current (2-wire sensor), max.</li> <li>Interrupts/diagnostics/status information</li> <li>Diagnostics function</li> <li>Alarms         <ul> <li>Diagnostic alarm</li> <li>Diagnostic alarm</li> <li>Diagnostic information readable</li> <li>Monitoring the supply voltage</li> <li>parameterizable</li> </ul> </li> </ul>	1.5 mA Yes Yes Yes Yes Yes
<ul> <li>permissible quiescent current (2-wire sensor), max.</li> <li>Interrupts/diagnostics/status information</li> <li>Diagnostics function</li> <li>Alarms         <ul> <li>Diagnostic alarm</li> <li>Diagnoses</li> <li>Diagnostic information readable</li> <li>Monitoring the supply voltage</li></ul></li></ul>	1.5 mA Yes Yes Yes Yes Yes No Yes; Module-by-module, optional protective circuit for preventing wire-
<ul> <li>permissible quiescent current (2-wire sensor), max.</li> <li>Interrupts/diagnostics/status information</li> <li>Diagnostics function</li> <li>Alarms         <ul> <li>Diagnostic alarm</li> <li>Diagnoses</li> <li>Diagnostic information readable</li> <li>Monitoring the supply voltage</li></ul></li></ul>	1.5 mA Yes Yes Yes Yes Yes No Yes; Module-by-module, optional protective circuit for preventing wire- break diagnostics in the case of simple encoder contacts: 25 kOhm to
<ul> <li>permissible quiescent current (2-wire sensor), max.</li> <li>Interrupts/diagnostics/status information</li> <li>Diagnostics function</li> <li>Alarms         <ul> <li>Diagnostic alarm</li> <li>Diagnostic information readable</li> <li>Monitoring the supply voltage</li></ul></li></ul>	1.5 mA Yes Yes Yes Yes No Yes; Module-by-module, optional protective circuit for preventing wire- break diagnostics in the case of simple encoder contacts: 25 kOhm to 45 kOhm
<ul> <li>permissible quiescent current (2-wire sensor), max.</li> <li>Interrupts/diagnostics/status information</li> <li>Diagnostics function</li> <li>Alarms         <ul> <li>Diagnostic alarm</li> <li>Diagnostic information readable</li> <li>Monitoring the supply voltage                 <ul></ul></li></ul></li></ul>	1.5 mA Yes Yes Yes Yes No Yes; Module-by-module, optional protective circuit for preventing wire- break diagnostics in the case of simple encoder contacts: 25 kOhm to 45 kOhm No
<ul> <li>permissible quiescent current (2-wire sensor), max.</li> <li>Interrupts/diagnostics/status information</li> <li>Diagnostics function</li> <li>Alarms         <ul> <li>Diagnostic alarm</li> <li>Diagnostic information readable</li> <li>Monitoring the supply voltage                 <ul></ul></li></ul></li></ul>	1.5 mA Yes Yes Yes Yes No Yes; Module-by-module, optional protective circuit for preventing wire- break diagnostics in the case of simple encoder contacts: 25 kOhm to 45 kOhm No
<ul> <li>permissible quiescent current (2-wire sensor), max.</li> <li>Interrupts/diagnostics/status information</li> <li>Diagnostics function</li> <li>Alarms         <ul> <li>Diagnostic alarm</li> <li>Diagnostic information readable</li> <li>Monitoring the supply voltage                 <ul></ul></li></ul></li></ul>	1.5 mA Yes Yes Yes Yes Yes No Yes; Module-by-module, optional protective circuit for preventing wire- break diagnostics in the case of simple encoder contacts: 25 kOhm to 45 kOhm No Yes
<ul> <li>permissible quiescent current (2-wire sensor), max.</li> <li>Interrupts/diagnostics/status information</li> <li>Diagnostics function</li> <li>Alarms         <ul> <li>Diagnostic alarm</li> <li>Diagnostic information readable</li> <li>Monitoring the supply voltage</li> <li>parameterizable</li> <li>Monitoring of encoder power supply</li> <li>Wire-break</li> <li>Short-circuit</li> <li>Group error</li> <li>Diagnostics indication LED</li> <li>Monitoring of the supply voltage (PWR-LED)</li> </ul> </li> </ul>	1.5 mA Yes Yes Yes Yes Yes No Yes; Module-by-module, optional protective circuit for preventing wire- break diagnostics in the case of simple encoder contacts: 25 kOhm to 45 kOhm No Yes Yes; green PWR LED
<ul> <li>permissible quiescent current (2-wire sensor), max.</li> <li>Interrupts/diagnostics/status information</li> <li>Diagnostics function</li> <li>Alarms         <ul> <li>Diagnostic alarm</li> <li>Diagnostic information readable</li> <li>Monitoring the supply voltage</li> <li>parameterizable</li> <li>Monitoring of encoder power supply</li> <li>Wire-break</li> </ul> </li> <li>Short-circuit</li> <li>Group error</li> <li>Diagnostics indication LED</li> <li>Monitoring of the supply voltage (PWR-LED)</li> <li>Channel status display</li> </ul>	1.5 mA Yes Yes Yes Yes No Yes; Module-by-module, optional protective circuit for preventing wire- break diagnostics in the case of simple encoder contacts: 25 kOhm to 45 kOhm No Yes Yes
<ul> <li>permissible quiescent current (2-wire sensor), max.</li> <li>Interrupts/diagnostics/status information</li> <li>Diagnostics function</li> <li>Alarms         <ul> <li>Diagnostic alarm</li> <li>Diagnostic information readable</li> <li>Monitoring the supply voltage</li> <li>parameterizable</li> <li>Monitoring of encoder power supply</li> <li>Wire-break</li> </ul> </li> <li>Short-circuit</li> <li>Group error</li> <li>Diagnostics indication LED</li> <li>Monitoring of the supply voltage (PWR-LED)</li> <li>Channel status display</li> <li>for channel diagnostics</li> </ul>	1.5 mA Yes Yes Yes Yes Yes No Yes; Module-by-module, optional protective circuit for preventing wire- break diagnostics in the case of simple encoder contacts: 25 kOhm to 45 kOhm No Yes Yes
<ul> <li>permissible quiescent current (2-wire sensor), max.</li> <li>Interrupts/diagnostics/status information</li> <li>Diagnostics function</li> <li>Alarms         <ul> <li>Diagnostic alarm</li> <li>Diagnostic information readable</li> <li>Monitoring the supply voltage</li> <li>parameterizable</li> <li>Monitoring of encoder power supply</li> <li>Wire-break</li> </ul> </li> <li>Short-circuit</li> <li>Group error</li> <li>Diagnostics indication LED</li> <li>Monitoring of the supply voltage (PWR-LED)</li> <li>Channel status display</li> <li>for channel diagnostics</li> <li>for module diagnostics</li> </ul>	1.5 mA Yes Yes Yes Yes Yes No Yes; Module-by-module, optional protective circuit for preventing wire- break diagnostics in the case of simple encoder contacts: 25 kOhm to 45 kOhm No Yes Yes
<ul> <li>permissible quiescent current (2-wire sensor), max.</li> <li>Interrupts/diagnostics/status information</li> <li>Diagnostics function</li> <li>Alarms <ul> <li>Diagnostic alarm</li> </ul> </li> <li>Diagnostic information readable</li> <li>Monitoring the supply voltage <ul> <li>parameterizable</li> <li>Monitoring of encoder power supply</li> <li>Wire-break</li> </ul> </li> <li>Short-circuit <ul> <li>Group error</li> </ul> </li> <li>Diagnostics indication LED <ul> <li>Monitoring of the supply voltage (PWR-LED)</li> <li>Channel status display</li> <li>for channel diagnostics</li> <li>for module diagnostics</li> </ul> </li> </ul>	1.5 mA Yes Yes Yes Yes Yes No Yes; Module-by-module, optional protective circuit for preventing wire- break diagnostics in the case of simple encoder contacts: 25 kOhm to 45 kOhm No Yes Yes
<ul> <li>permissible quiescent current (2-wire sensor), max.</li> <li>Interrupts/diagnostics/status information</li> <li>Diagnostics function</li> <li>Alarms         <ul> <li>Diagnostic alarm</li> <li>Diagnostic information readable</li> <li>Monitoring the supply voltage</li> <li>parameterizable</li> <li>Monitoring of encoder power supply</li> <li>Wire-break</li> </ul> </li> <li>Short-circuit         <ul> <li>Group error</li> <li>Diagnostics indication LED</li> <li>Channel status display</li> <li>for channel diagnostics</li> <li>for module diagnostics</li> </ul> </li> <li>Potential separation channels         <ul> <li>between the channels</li> <li>between the channels</li> </ul> </li> </ul>	1.5 mA Yes Yes Yes Yes No Yes; Module-by-module, optional protective circuit for preventing wire- break diagnostics in the case of simple encoder contacts: 25 kOhm to 45 kOhm No Yes Yes; green PWR LED Yes; green LED Yes; green LED No Yes; green/red DIAG LED
<ul> <li>permissible quiescent current (2-wire sensor), max.</li> <li>Interrupts/diagnostics/status information</li> <li>Diagnostics function</li> <li>Alarms         <ul> <li>Diagnostic alarm</li> <li>Diagnostic information readable</li> <li>Monitoring the supply voltage</li> <li>parameterizable</li> <li>Monitoring of encoder power supply</li> <li>Wire-break</li> </ul> </li> <li>Short-circuit         <ul> <li>Group error</li> <li>Diagnostics indication LED</li> <li>Monitoring of the supply voltage (PWR-LED)</li> <li>Channel status display</li> <li>for channel diagnostics</li> <li>for module diagnostics</li> </ul> </li> <li>Potential separation channels         <ul> <li>between the channels</li> <li>between the channels and backplane bus</li> </ul> </li> </ul>	1.5 mA Yes Yes Yes Yes No Yes; Module-by-module, optional protective circuit for preventing wire- break diagnostics in the case of simple encoder contacts: 25 kOhm to 45 kOhm No Yes Yes; green PWR LED Yes; green LED No Yes; green/red DIAG LED
<ul> <li>permissible quiescent current (2-wire sensor), max.</li> <li>Interrupts/diagnostics/status information</li> <li>Diagnostics function</li> <li>Alarms         <ul> <li>Diagnostic alarm</li> <li>Diagnostic information readable</li> <li>Monitoring the supply voltage</li> <li>parameterizable</li> <li>Monitoring of encoder power supply</li> <li>Wire-break</li> </ul> </li> <li>Short-circuit         <ul> <li>Group error</li> <li>Diagnostics indication LED</li> <li>Channel status display</li> <li>for channel diagnostics</li> <li>for module diagnostics</li> </ul> </li> <li>Potential separation channels         <ul> <li>between the channels</li> <li>between the channels</li> </ul> </li> </ul>	1.5 mA Yes Yes Yes Yes Yes No Yes; Module-by-module, optional protective circuit for preventing wire- break diagnostics in the case of simple encoder contacts: 25 kOhm to 45 kOhm No Yes Yes; green PWR LED Yes; green LED No Yes; green/red DIAG LED
<ul> <li>permissible quiescent current (2-wire sensor), max.</li> <li>Interrupts/diagnostics/status information</li> <li>Diagnostics function</li> <li>Alarms         <ul> <li>Diagnostic alarm</li> <li>Diagnostic information readable</li> <li>Monitoring the supply voltage</li> <li>parameterizable</li> <li>Monitoring of encoder power supply</li> <li>Wire-break</li> </ul> </li> <li>Short-circuit         <ul> <li>Group error</li> <li>Diagnostics indication LED</li> <li>Channel status display</li> <li>for channel diagnostics</li> <li>for module diagnostics</li> <li>for module diagnostics</li> </ul> </li> <li>Potential separation channels         <ul> <li>between the channels</li> <li>between the channels and backplane bus</li> <li>between the channels and the power supply of the</li> </ul> </li> </ul>	1.5 mA Yes Yes Yes Yes Yes No Yes; Module-by-module, optional protective circuit for preventing wire- break diagnostics in the case of simple encoder contacts: 25 kOhm to 45 kOhm No Yes Yes; green PWR LED Yes; green LED No Yes; green/red DIAG LED
<ul> <li>permissible quiescent current (2-wire sensor), max.</li> <li>Interrupts/diagnostics/status information</li> <li>Diagnostics function</li> <li>Alarms <ul> <li>Diagnostic alarm</li> </ul> </li> <li>Diagnostic information readable</li> <li>Monitoring the supply voltage <ul> <li>parameterizable</li> <li>Monitoring of encoder power supply</li> <li>Wire-break</li> </ul> </li> <li>Short-circuit <ul> <li>Group error</li> </ul> </li> <li>Diagnostics indication LED</li> <li>Monitoring of the supply voltage (PWR-LED)</li> <li>Channel status display</li> <li>for channel diagnostics</li> <li>for module diagnostics</li> <li>for module diagnostics</li> </ul> <li>Potential separation channels <ul> <li>between the channels and backplane bus</li> <li>between the channels and the power supply of the electronics</li> </ul> </li>	1.5 mA         Yes         No         Yes         No         Yes         No
<ul> <li>permissible quiescent current (2-wire sensor), max.</li> <li>Interrupts/diagnostics/status information</li> <li>Diagnostics function</li> <li>Alarms         <ul> <li>Diagnostic alarm</li> <li>Diagnostic information readable</li> <li>Monitoring the supply voltage</li> <li>parameterizable</li> <li>Monitoring of encoder power supply</li> <li>Wire-break</li> </ul> </li> <li>Short-circuit         <ul> <li>Group error</li> </ul> </li> <li>Diagnostics indication LED</li> <li>Monitoring of the supply voltage (PWR-LED)</li> <li>Channel status display</li> <li>for channel diagnostics</li> <li>for module diagnostics</li> </ul> <li>Potential separation channels         <ul> <li>between the channels and backplane bus</li> <li>between the channels and backplane bus</li> <li>between the channels and the power supply of the electronics</li> </ul> </li>	1.5 mA Yes Yes Yes Yes Yes No Yes; Module-by-module, optional protective circuit for preventing wire- break diagnostics in the case of simple encoder contacts: 25 kOhm to 45 kOhm No Yes Yes; green PWR LED Yes; green LED No Yes; green/red DIAG LED
<ul> <li>permissible quiescent current (2-wire sensor), max.</li> <li>Interrupts/diagnostics/status information</li> <li>Diagnostics function</li> <li>Alarms <ul> <li>Diagnostic alarm</li> </ul> </li> <li>Diagnostic information readable</li> <li>Monitoring the supply voltage <ul> <li>parameterizable</li> <li>Monitoring of encoder power supply</li> <li>Wire-break</li> </ul> </li> <li>Short-circuit <ul> <li>Group error</li> </ul> </li> <li>Diagnostics indication LED</li> <li>Monitoring of the supply voltage (PWR-LED)</li> <li>Channel status display</li> <li>for channel diagnostics</li> <li>for module diagnostics</li> <li>for module diagnostics</li> </ul> <li>Potential separation channels <ul> <li>between the channels and backplane bus</li> <li>between the channels and the power supply of the electronics</li> </ul> </li>	1.5 mA         Yes         No         Yes         No         Yes         No

Ambient conditions	
Ambient temperature during operation	
<ul> <li>horizontal installation, min.</li> </ul>	-30 °C; < 0 °C as of FS02
<ul> <li>horizontal installation, max.</li> </ul>	60 °C
<ul> <li>vertical installation, min.</li> </ul>	-30 °C; < 0 °C as of FS02
<ul> <li>vertical installation, max.</li> </ul>	50 °C
Altitude during operation relating to sea level	
<ul> <li>Installation altitude above sea level, max.</li> </ul>	5 000 m; Restrictions for installation altitudes > 2 000 m, see manual
Dimensions	
Width	15 mm
Height	73 mm
Depth	58 mm
Weights	
Weight, approx.	28 g
last modified:	9/24/2021 🖸