Data sheet

6ES7523-1BP50-0AA0



SIMATIC S7-1500 digital input/output module, DI 32x24VDC BA SNK / SRC, 32 channels in groups of 16, input delay typ. 3.2 ms input type 3 (IEC 61131), sinking/sourcing input, DQ 32XDC 24V/0.3A SNK BA; 32 channels in groups of 16; 2 A per group at 60 °C; sourcing output; 35 mm wide; cables and terminal blocks to be ordered separately as accessories

General information	
Product type designation	DI 32 x 24 V DC / DQ 32 x 24 V DC/0.3A SNK BA
HW functional status	From FS01
Firmware version	V1.0.0
 FW update possible 	Yes
Product function	
I&M data	Yes; I&M0 to I&M3
 Isochronous mode 	No
 Prioritized startup 	No
Engineering with	
 STEP 7 TIA Portal configurable/integrated from version 	V16 with HSP 0319 / V17
 STEP 7 configurable/integrated from version 	V5.5 SP3 / -
 PROFIBUS from GSD version/GSD revision 	V1.0 / V5.1
 PROFINET from GSD version/GSD revision 	V2.35 / -
Operating mode	
• DI	Yes
Counter	No
• DQ	Yes
 DQ with energy-saving function 	No
• PWM	No
 Cam control (switching at comparison values) 	No
 Oversampling 	No
• MSI	Yes
• MSO	Yes
 Integrated operating cycle counter 	No
Supply voltage	
Rated value (DC)	24 V
permissible range, lower limit (DC)	19.2 V
permissible range, upper limit (DC)	28.8 V
Reverse polarity protection	Yes; Through internal protection with 4 A per group
external protection for power supply lines (recommendation)	input side: 24 V DC/4 A miniature circuit breaker with type B or C tripping characteristic; output side: 24 V DC/6 A miniature circuit breaker with type B tripping characteristic
Input current	
Current consumption, max.	45 mA; without load
output voltage / header	
Rated value (DC)	24 V
Power	
Power available from the backplane bus	0.6 W
Power loss	

Power loss, typ.	4.7 W
Digital inputs	
Number of digital inputs	32
Digital inputs, parameterizable	No
Source/sink input	Yes
Input characteristic curve in accordance with IEC 61131,	Yes
type 3	
Number of simultaneously controllable inputs	
 Number of simultaneously controllable inputs 	32
horizontal installation	
— up to 60 °C, max.	32
vertical installation	
— up to 40 °C, max.	16
Input voltage	
Rated value (DC)	24 V
• for signal "0"	-5 +5 V (reference potential is COM)
• for signal "1"	-1130 V; +11 +30 V (reference potential is COM)
Input current	
• for signal "1", typ.	2.7 mA
Input delay (for rated value of input voltage)	
for standard inputs	Ne
— parameterizable	No 2 mg
— at "0" to "1", min.	3 ms
— at "0" to "1", max.	4 ms
— at "1" to "0", min.	3 ms
— at "1" to "0", max.	4 ms
for interrupt inputs — parameterizable	No
for technological functions	INO
— parameterizable	No
Cable length	NO
• shielded, max.	1 000 m
unshielded, max.	600 m
Digital outputs	330 111
	Transistor
Type of digital output	Transistor
Type of digital output Number of digital outputs	32
Type of digital output Number of digital outputs Current-sinking	32 Yes
Type of digital output Number of digital outputs Current-sinking Current-sourcing	32 Yes No
Type of digital output Number of digital outputs Current-sinking Current-sourcing Digital outputs, parameterizable	32 Yes No No
Type of digital output Number of digital outputs Current-sinking Current-sourcing	32 Yes No
Type of digital output Number of digital outputs Current-sinking Current-sourcing Digital outputs, parameterizable	32 Yes No No No; external fusing necessary, max. 4 A per group, tripping
Type of digital output Number of digital outputs Current-sinking Current-sourcing Digital outputs, parameterizable Short-circuit protection	32 Yes No No No; external fusing necessary, max. 4 A per group, tripping characteristic type B or C
Type of digital output Number of digital outputs Current-sinking Current-sourcing Digital outputs, parameterizable Short-circuit protection Limitation of inductive shutdown voltage to	32 Yes No No No No; external fusing necessary, max. 4 A per group, tripping characteristic type B or C L+ (-53 V)
Type of digital output Number of digital outputs Current-sinking Current-sourcing Digital outputs, parameterizable Short-circuit protection Limitation of inductive shutdown voltage to Controlling a digital input	32 Yes No No No No; external fusing necessary, max. 4 A per group, tripping characteristic type B or C L+ (-53 V)
Type of digital output Number of digital outputs Current-sinking Current-sourcing Digital outputs, parameterizable Short-circuit protection Limitation of inductive shutdown voltage to Controlling a digital input Switching capacity of the outputs	Yes No No No; external fusing necessary, max. 4 A per group, tripping characteristic type B or C L+ (-53 V) Yes
Type of digital output Number of digital outputs Current-sinking Current-sourcing Digital outputs, parameterizable Short-circuit protection Limitation of inductive shutdown voltage to Controlling a digital input Switching capacity of the outputs • with resistive load, max.	Yes No No No; external fusing necessary, max. 4 A per group, tripping characteristic type B or C L+ (-53 V) Yes 0.3 A
Type of digital output Number of digital outputs Current-sinking Current-sourcing Digital outputs, parameterizable Short-circuit protection Limitation of inductive shutdown voltage to Controlling a digital input Switching capacity of the outputs • with resistive load, max. • on lamp load, max.	Yes No No No; external fusing necessary, max. 4 A per group, tripping characteristic type B or C L+ (-53 V) Yes 0.3 A
Type of digital output Number of digital outputs Current-sinking Current-sourcing Digital outputs, parameterizable Short-circuit protection Limitation of inductive shutdown voltage to Controlling a digital input Switching capacity of the outputs • with resistive load, max. • on lamp load, max. Load resistance range	Yes No No No; external fusing necessary, max. 4 A per group, tripping characteristic type B or C L+ (-53 V) Yes 0.3 A 5 W
Type of digital output Number of digital outputs Current-sinking Current-sourcing Digital outputs, parameterizable Short-circuit protection Limitation of inductive shutdown voltage to Controlling a digital input Switching capacity of the outputs • with resistive load, max. • on lamp load, max. Load resistance range • lower limit • upper limit Output voltage	Yes No No No; external fusing necessary, max. 4 A per group, tripping characteristic type B or C L+ (-53 V) Yes $0.3 \text{ A} \\ 5 \text{ W}$ 80Ω $10 k\Omega$
Type of digital output Number of digital outputs Current-sinking Current-sourcing Digital outputs, parameterizable Short-circuit protection Limitation of inductive shutdown voltage to Controlling a digital input Switching capacity of the outputs • with resistive load, max. • on lamp load, max. Load resistance range • lower limit • upper limit Output voltage • for signal "1", min.	Yes No No No; external fusing necessary, max. 4 A per group, tripping characteristic type B or C L+ (-53 V) Yes 0.3 A 5 W
Type of digital output Number of digital outputs Current-sinking Current-sourcing Digital outputs, parameterizable Short-circuit protection Limitation of inductive shutdown voltage to Controlling a digital input Switching capacity of the outputs • with resistive load, max. • on lamp load, max. Load resistance range • lower limit • upper limit Output voltage • for signal "1", min. Output current	Yes No No No; external fusing necessary, max. 4 A per group, tripping characteristic type B or C L+ (-53 V) Yes $0.3 \text{ A} \\ 5 \text{ W}$ $80 \Omega \\ 10 \text{ k}\Omega$ $\text{M+ } (0.5 \text{ V})$
Type of digital output Number of digital outputs Current-sinking Current-sourcing Digital outputs, parameterizable Short-circuit protection Limitation of inductive shutdown voltage to Controlling a digital input Switching capacity of the outputs • with resistive load, max. • on lamp load, max. Load resistance range • lower limit • upper limit Output voltage • for signal "1", min. Output current • for signal "1" rated value	32 Yes No No No; external fusing necessary, max. 4 A per group, tripping characteristic type B or C L+ (-53 V) Yes $0.3 \text{ A} \\ 5 \text{ W} \\ 80 \Omega \\ 10 k\Omega \\ \text{M+ } (0.5 \text{ V}) \\ 0.3 \text{ A} \\ \text{O} \\ O$
Type of digital output Number of digital outputs Current-sinking Current-sourcing Digital outputs, parameterizable Short-circuit protection Limitation of inductive shutdown voltage to Controlling a digital input Switching capacity of the outputs • with resistive load, max. • on lamp load, max. Load resistance range • lower limit • upper limit Output voltage • for signal "1", min. Output current • for signal "1" rated value • for signal "1" permissible range, max.	32 Yes No No No; external fusing necessary, max. 4 A per group, tripping characteristic type B or C L+ (-53 V) Yes $0.3 \text{ A} \\ 5 \text{ W}$ $80 \Omega \\ 10 \text{ k}\Omega$ $M+ (0.5 \text{ V})$ $0.3 \text{ A} \\ 0.3 \text{ A}$
Type of digital output Number of digital outputs Current-sinking Current-sourcing Digital outputs, parameterizable Short-circuit protection Limitation of inductive shutdown voltage to Controlling a digital input Switching capacity of the outputs • with resistive load, max. • on lamp load, max. Load resistance range • lower limit • upper limit Output voltage • for signal "1", min. Output current • for signal "1" rated value • for signal "1" permissible range, max. • for signal "0" residual current, max.	32 Yes No No No; external fusing necessary, max. 4 A per group, tripping characteristic type B or C L+ (-53 V) Yes $0.3 \text{ A} \\ 5 \text{ W}$ $80 \Omega \\ 10 \text{ k}\Omega$ $M+ (0.5 \text{ V})$
Type of digital output Number of digital outputs Current-sinking Current-sourcing Digital outputs, parameterizable Short-circuit protection Limitation of inductive shutdown voltage to Controlling a digital input Switching capacity of the outputs • with resistive load, max. • on lamp load, max. Load resistance range • lower limit • upper limit Output voltage • for signal "1", min. Output current • for signal "1" rated value • for signal "1" residual current, max. Output delay with resistive load	Yes No No No; external fusing necessary, max. 4 A per group, tripping characteristic type B or C L+ (-53 V) Yes $0.3 \text{ A} \\ 5 \text{ W}$ $80 \Omega \\ 10 \text{ k}\Omega$ $M+ (0.5 \text{ V})$ $0.3 \text{ A} \\ 0.3 \text{ A}$ 0.5 mA
Type of digital output Number of digital outputs Current-sinking Current-sourcing Digital outputs, parameterizable Short-circuit protection Limitation of inductive shutdown voltage to Controlling a digital input Switching capacity of the outputs • with resistive load, max. • on lamp load, max. Load resistance range • lower limit • upper limit Output voltage • for signal "1", min. Output current • for signal "1" rated value • for signal "1" permissible range, max. • for signal "0" residual current, max. Output delay with resistive load • "0" to "1", max.	Yes No No No; external fusing necessary, max. 4 A per group, tripping characteristic type B or C L+ (-53 V) Yes $0.3 \text{ A} \\ 5 \text{ W}$ $80 \Omega \\ 10 \text{ k}\Omega$ $M+ (0.5 \text{ V})$ $0.3 \text{ A} \\ 0.5 \text{ mA}$
Type of digital output Number of digital outputs Current-sinking Current-sourcing Digital outputs, parameterizable Short-circuit protection Limitation of inductive shutdown voltage to Controlling a digital input Switching capacity of the outputs • with resistive load, max. • on lamp load, max. Load resistance range • lower limit • upper limit Output voltage • for signal "1", min. Output current • for signal "1" rated value • for signal "1" permissible range, max. • for signal "0" residual current, max. Output delay with resistive load • "0" to "1", max. • "1" to "0", max.	Yes No No No; external fusing necessary, max. 4 A per group, tripping characteristic type B or C L+ (-53 V) Yes $0.3 \text{ A} \\ 5 \text{ W}$ $80 \Omega \\ 10 \text{ k}\Omega$ $M+ (0.5 \text{ V})$ $0.3 \text{ A} \\ 0.3 \text{ A}$ 0.5 mA
Type of digital output Number of digital outputs Current-sinking Current-sourcing Digital outputs, parameterizable Short-circuit protection Limitation of inductive shutdown voltage to Controlling a digital input Switching capacity of the outputs • with resistive load, max. • on lamp load, max. Load resistance range • lower limit • upper limit Output voltage • for signal "1", min. Output current • for signal "1" rated value • for signal "1" permissible range, max. • for signal "0" residual current, max. Output delay with resistive load • "0" to "1", max. • "1" to "0", max. Parallel switching of two outputs	Yes No No No; external fusing necessary, max. 4 A per group, tripping characteristic type B or C L+ (-53 V) Yes $0.3 \text{ A} \\ 5 \text{ W}$ $80 \Omega \\ 10 \text{ k}\Omega$ $M+ (0.5 \text{ V})$ $0.3 \text{ A} \\ 0.5 \text{ mA}$ $100 \text{ µs} \\ 500 \text{ µs}$
Type of digital output Number of digital outputs Current-sinking Current-sourcing Digital outputs, parameterizable Short-circuit protection Limitation of inductive shutdown voltage to Controlling a digital input Switching capacity of the outputs • with resistive load, max. • on lamp load, max. Load resistance range • lower limit • upper limit Output voltage • for signal "1", min. Output current • for signal "1" rated value • for signal "1" permissible range, max. • for signal "0" residual current, max. Output delay with resistive load • "0" to "1", max. • "1" to "0", max. Parallel switching of two outputs • for logic links	Yes No No No; external fusing necessary, max. 4 A per group, tripping characteristic type B or C L+ (-53 V) Yes $0.3 \text{ A} \\ 5 \text{ W}$ $80 \Omega \\ 10 \text{ k}\Omega$ $M+ (0.5 \text{ V})$ $0.3 \text{ A} \\ 0.5 \text{ mA}$ $100 \mu\text{s} \\ 500 \mu\text{s}$
Type of digital output Number of digital outputs Current-sinking Current-sourcing Digital outputs, parameterizable Short-circuit protection Limitation of inductive shutdown voltage to Controlling a digital input Switching capacity of the outputs • with resistive load, max. • on lamp load, max. Load resistance range • lower limit • upper limit Output voltage • for signal "1", min. Output current • for signal "1" rated value • for signal "1" permissible range, max. • for signal "0" residual current, max. Output delay with resistive load • "0" to "1", max. • "1" to "0", max. Parallel switching of two outputs • for logic links • for uprating	Yes No No No; external fusing necessary, max. 4 A per group, tripping characteristic type B or C L+ (-53 V) Yes $0.3 \text{ A} \\ 5 \text{ W}$ $80 \Omega \\ 10 \text{ k}\Omega$ $M+ (0.5 \text{ V})$ $0.3 \text{ A} \\ 0.3 \text{ M}$ 0.5 mA
Type of digital output Number of digital outputs Current-sinking Current-sourcing Digital outputs, parameterizable Short-circuit protection Limitation of inductive shutdown voltage to Controlling a digital input Switching capacity of the outputs • with resistive load, max. • on lamp load, max. Load resistance range • lower limit • upper limit Output voltage • for signal "1", min. Output current • for signal "1" rated value • for signal "1" permissible range, max. • for signal "0" residual current, max. Output delay with resistive load • "0" to "1", max. • "1" to "0", max. Parallel switching of two outputs • for logic links • for redundant control of a load	Yes No No No; external fusing necessary, max. 4 A per group, tripping characteristic type B or C L+ (-53 V) Yes $0.3 \text{ A} \\ 5 \text{ W}$ $80 \Omega \\ 10 \text{ k}\Omega$ $M+ (0.5 \text{ V})$ $0.3 \text{ A} \\ 0.5 \text{ mA}$ $100 \mu\text{s} \\ 500 \mu\text{s}$
Type of digital output Number of digital outputs Current-sinking Current-sourcing Digital outputs, parameterizable Short-circuit protection Limitation of inductive shutdown voltage to Controlling a digital input Switching capacity of the outputs • with resistive load, max. • on lamp load, max. Load resistance range • lower limit • upper limit Output voltage • for signal "1", min. Output current • for signal "1" rated value • for signal "1" permissible range, max. • for signal "0" residual current, max. Output delay with resistive load • "0" to "1", max. • "1" to "0", max. Parallel switching of two outputs • for logic links • for uprating	Yes No No No; external fusing necessary, max. 4 A per group, tripping characteristic type B or C L+ (-53 V) Yes $0.3 \text{ A} \\ 5 \text{ W}$ $80 \Omega \\ 10 \text{ k}\Omega$ $M+ (0.5 \text{ V})$ $0.3 \text{ A} \\ 0.3 \text{ M}$ 0.5 mA

a with industive lead, may	0.5 Hz; According to IFC 60047.5.1. DC 13
with inductive load, max.	0.5 Hz; According to IEC 60947-5-1, DC-13
• on lamp load, max.	10 Hz
Total current of the outputs	0.0 A
Current per channel, max.	0.3 A
Current per group, max.	2 A
Current per module, max.	4 A
Total current of the outputs (per module)	
horizontal installation	
— up to 60 °C, max.	4 A
vertical installation	
— up to 40 °C, max.	4 A
Cable length	
• shielded, max.	1 000 m
unshielded, max.	600 m
Encoder	
Connectable encoders	
• 2-wire sensor	Yes
 permissible quiescent current (2-wire sensor), 	1.5 mA
max.	
Interrupts/diagnostics/status information	
Diagnostics function	No
Substitute values connectable	No
Alarms	
Diagnostic alarm	No
Maintenance interrupt	No
Hardware interrupt	No
Diagnoses	
Monitoring the supply voltage	No
Wire-break	No
Short-circuit	No
Group error	No
Diagnostics indication LED	110
• RUN LED	Yes; green LED
• ERROR LED	Yes; red LED
MAINT LED	No
Monitoring of the supply voltage (PWR-LED)	Yes; via SIMATIC TOP connect connection module
Channel status display	Yes; via SIMATIC TOP connect connection module
for channel diagnostics	No
for module diagnostics	No
	110
Potential separation	
Potential separation channels	
 between the channels 	No
 between the channels, in groups of 	16; 32 when using SIMATIC TOP connect connection module
between the channels and backplane bus	Yes
Isolation	
Isolation tested with	707 V DC (type test)
Ambient conditions	
Ambient temperature during operation	
horizontal installation, min.	-30 °C
horizontal installation, max.	60 °C
vertical installation, min.	-30 °C
vertical installation, min. vertical installation, max.	40 °C
Altitude during operation relating to sea level	10 0
Installation altitude above sea level, max.	5 000 m
	O OOO III
Dimensions	
Width	35 mm
Height	147 mm
Height Depth	
_	147 mm
Depth	147 mm
Depth Weights Weight, approx.	147 mm 129 mm
Depth Weights	147 mm 129 mm

last modified: 1/16/2021 🖸